



MONTGOMERY COUNTY EXECUTIVE REGULATION

Offices of the County Executive, 101 Monroe Street, Rockville, Maryland 20850

Subject: Adoption of the 2017 National Electrical Code	Number: 23-19
Originating Department: Department of Permitting Services	Effective Date: October 22, 2019

Montgomery County Regulation on:

ADOPTION OF THE 2017 NATIONAL ELECTRICAL CODE

DEPARTMENT OF PERMITTING SERVICES

Issued by County Executive
Regulation # 23-19
COMCOR 17.02.01

Authority: Code Section 17-2 and 17-3
Supersedes: Executive Regulation No. 6-16AM
Council Review: Method 2 under Code Section 2A- 15
Register Vol. 36, Issue 7

Comment Deadline: July 31, 2019
Effective date: October 22, 2019
Sunset date: None

SUMMARY:

This regulation adopts the National Electrical Code, 2017 Edition, with local amendments. This regulation applies to all electrical equipment, installations and activities within the County.

ADDRESSES: Department of Permitting Services
255 Rockville Pike, Second Floor
Rockville, Maryland 20850

STAFF CONTACT: Hemal Mustafa, Division Chief
240-777-6226

Anthony Toussaint, Senior Permitting Specialist
240-777-6204

BACKGROUND:

This regulation supersedes Executive Regulation # 6-16AM which adopted the 2014 edition of the National Electrical Code. This regulation adopts the 2017 edition of the National Electrical Code which is used nationwide. The 2017 National Electrical Code was adopted by the National Fire Protection Association at its Association Technical meeting held June 13-16, 2016 in Las Vegas, NV.



MONTGOMERY COUNTY EXECUTIVE REGULATION

Offices of the County Executive, 101 Monroe Street, Rockville, Maryland 20850

Subject: Adoption of the 2017 National Electrical Code

Number: 23-19

Originating Department: Department of Permitting Services

Effective Date: ~~October 14, 2019~~
October 22, 2019

COMCOR 17.02.01 Adoption of the 2017 National Electric Code

17.02.01.01

Under the procedures authorized in Chapter 17, Sections 17-2 and 17-3, Regulations and Adoption of Basic Electrical Code, Montgomery County Code, as amended (the code), the following executive regulation applies to all electrical equipment, installations, and activities within Montgomery County.

17.02.01.02

Unless otherwise noted, all references to the National Electrical Code (hereafter referred to as NEC) contained in this regulation are to The National Electrical Code (NFPA No 70-2017), adopted by the National Fire Protection Association at its Association Technical meeting held June 13-16, 2016, in Las Vegas, NV. This regulation supersedes all previously promulgated references to the NEC.

17.02.01.03

The 2017 NEC is adopted as the Electrical Code of Montgomery County, and all electrical installations and equipment must meet the standards and requirements set forth in that code or in this regulation. The 2017 NEC is incorporated by reference as if that code were fully set forth with the following additions, deletions, and amendments.

Whenever the provisions of this regulation and those of the NEC are in conflict, the provisions of this regulation will govern and be enforced in the County. The Director is solely responsible for the interpretation of these regulations as amended.

17.02.01.04

ARTICLE 100 DEFINITIONS

Add the following definition after the definition of "Appliance," as provided in Article 100:
Appliance, fixed: An appliance which is fastened or otherwise secured at a specific location.

Amend the definition of "Building" as follows:

Building: A structure which stands alone or which is separated from adjoining structures by fire walls conforming to the definition and requirements of ICC International Building Code for fire walls.

17.02.01.05

Section 210.5(C) add the following to article:

210.5(C). Ungrounded Conductor. Where installed in raceways, as open work or as concealed knob-and-tube work. Ungrounded conductors must be identified by a color other than as specified in (A) or (B) above. All ungrounded conductors of the same color must be connected to the same ungrounded feeder conductor, and the conductors for systems of different voltages must be of different colors.



MONTGOMERY COUNTY EXECUTIVE REGULATION

Offices of the County Executive, 101 Monroe Street, Rockville, Maryland 20850

Subject: Adoption of the 2017 National Electrical Code

Number: 23-19

Originating Department: Department of Permitting Services

Effective Date: October 14, 2019
October 22, 2019

Exception. As permitted in Section 200.7.

For basic single- and three-phase wiring systems of 120/208/240 volts: 3-wire circuits must use 1 black, 1 white, and 1 red wire; 4-wire circuits must use 1 black, 1 white, 1 red, and 1 blue wire. For basic single- and three-phase wiring systems of 277/480 volts, the colors gray, brown, orange, and yellow must be used.

17.02.01.06

Section 210.11. Add the following sentence:

Each fixed appliance must be served by an individual branch circuit except for electric baseboard heaters, appurtenant equipment to furnaces, such as humidifiers and electronic air cleaners, and other equipment having motors rated 1/4 hp or less.

17.02.01.07

Section 210.19(A)(3). Delete and substitute the following:

Section 210.19(A)(3). Each wall-mounted oven and each counter-mounted cooking unit must be served by an individual circuit of copper wire. The conductor size is based on 100 percent of the nameplate rating of the unit, but cannot be smaller than size No. 10.

17.02.01.08

Section 210.52(A). Add the following new subsection:

(5) General lighting branch circuits in dwellings must not have more than 12 power-consuming outlets. A duplex receptacle is considered to be one outlet. Smoke detectors are not considered power-consuming devices for counting purposes.

Section 210.52(B). Add the following as the first paragraph:

A general appliance branch circuit in a dwelling must not have more than eight receptacle outlets. A duplex receptacle is considered to be one outlet.

Section 210.52(E)(1). Add the following sentence:

When an addition is made to an existing dwelling which has no outside ground-fault circuit-interrupter (GFCI) receptacle, a GFCI protected receptacle, accessible at grade level, must be installed on the outside of the new addition.

Section 210.52(E)(3). Balconies, Decks, and Porches. Add the following paragraph at the end:

If altered, existing balconies, decks, and porches that are attached to the dwelling unit, accessible from inside the dwelling unit, and greater than 20 square feet, must have at least one receptacle outlet accessible from the balcony, deck, or porch.



MONTGOMERY COUNTY EXECUTIVE REGULATION

Offices of the County Executive, 101 Monroe Street, Rockville, Maryland 20850

Subject: Adoption of the 2017 National Electrical Code	Number: 23-19
Originating Department: Department of Permitting Services	Effective Date: October 14, 2019 October 22, 2019

17.02.01.09

Section 230.70(A)(1). Add the following:

In new buildings without direct grade access to the Main Building Electrical Equipment, excluding one and two-family dwellings, a shunt trip to disconnect the electrical service to the building must be provided as follows:

- (a) In the Fire Command Center, where a Fire Command Center is in the building.
- (b) At the fire alarm annunciator, where there is no Fire Command Center.
- (c) In an appropriately sized and weatherproof fire department access box on the address side of the building, where there is no fire alarm annunciator or Fire Command Center.

In existing buildings, excluding one and two-family dwellings, where there are significant upgrades to the building electrical service, such as modifying or replacing the switchgear, a disconnecting means must be provided as for new installations.

17.02.01.10

Section 250.50. Add the following text as the first and second sentence to Section 250.50:

All new structures, both residential and commercial, require a concrete encased electrode to be used as the principle grounding element. The concrete encased electrode must be installed under Section 250.52(A)(3) and the reinforcing rods or copper conductors or both utilized in the installation require a minimum of 0.61mm (2 feet) of accessible length after installation.

17.02.01.11

Section 310.15(B) Tables. Delete the first sentence and substitute with the following:

The minimum size of conductors must be as shown in Table 310.15(B)(16) through Table 310.15(B)(19), as modified by Table 310.15(B)(1) through (B)(7), except that the minimum size of aluminum and copper-clad aluminum conductors must be No. 2. The use of aluminum conductors is limited to service entrance and feeder applications only.

Note: No exceptions to sizes of wire as enumerated here or elsewhere in the code will be allowed in the case of aluminum conductors.

17.02.01.12

Section 410.36(B). Delete and substitute the following:

Suspended Ceilings. All fixtures installed in suspended ceilings must be supported from the building structure directly. If wire is used for this purpose, no less than 2 separate wires of size No. 12 (or larger) steel must be used. These wires must extend from opposite corners of the fixture with each wire independently attached to the building structure.



MONTGOMERY COUNTY EXECUTIVE REGULATION

Offices of the County Executive, 101 Monroe Street, Rockville, Maryland 20850

Subject: Adoption of the 2017 National Electrical Code	Number: 23-19
Originating Department: Department of Permitting Services	Effective Date: October 14, 2019 October 22, 2019

Exception: If the fixture is circular, and not more than 24 inches in diameter, at least one wire of No. 12 steel or larger must be used to support the fixture.

17.02.01.13

Section 440.62(C). Delete and substitute the following:

Each individual room air-conditioning unit, regardless of its current rating, must be served by an individual circuit of not less than No. 12 copper wire, and must terminate in a single receptacle.

17.02.01.14

Section 700.18. Add two new paragraphs as follows:

Any building in which standpipes are installed must have one 30-ampere, 120-volt circuit installed for each standpipe riser, supplied from the legally required stand by system. The wiring method for exposed work must be galvanized, threaded metal conduit. Boxes must be metal, weatherproof types with gasketed flap-door covers and threaded hubs. The wiring method for concealed work must be metal conduit with appropriate galvanized boxes having gasketed flap-door covers suitable for fire department use. The weatherproof cover must be suitable for receiving the L5-20R NEMA type twist-lock receptacle without damage (e.g., Bell #128-226 cover or equivalent).

Supply wiring must be at least 75 degrees C-type wire. One single 20-ampere three-wire twistlock receptacle (NEMA L5-20R) must be installed at least as high as, and with a 2-foot offset from EACH HOSE VALVE CONNECTION. Each outlet box must be painted "fire-alarm red" in color and be marked "Only for Fire Department Use."

Note: This Section supersedes the requirements of Table 210.21(B)(2).

17.02.01.15

Electrical Maintenance Inspection Required

All commercially owned and occupied buildings or structures as defined in the International Energy Conservation Code must have a Maintenance Inspection of the Electrical Service Equipment every three (3) calendar years. The Maintenance Inspection must include Main Building Electrical Equipment such as all switchgear, bus duct, and feeders that supply power to the structure, and must be performed by a Master Electrician licensed by Montgomery County. The Master Electrician must promptly prepare a written Maintenance Inspection report, identifying the equipment inspected and the condition to be corrected or repaired, and deliver a copy to the Building Owner within 10-days of the date of inspection. Any deficiencies in the Electrical Service Equipment must be corrected or repaired within 60 days of receipt of the Maintenance Inspection report. A copy of the Maintenance inspection report must be made available to the Department of Permitting Services upon request.



MONTGOMERY COUNTY EXECUTIVE REGULATION

Offices of the County Executive, 101 Monroe Street, Rockville, Maryland 20850

Subject: Adoption of the 2017 National Electrical Code

Number: 23-19

Originating Department: Department of Permitting Services

Effective Date: October 14, 2019
October 22, 2019

17.02.01.16 Severability


The provisions of this regulation are severable. If a court of competent jurisdiction holds that a provision is invalid or inapplicable, the remainder of the regulation remains in effect.



Marc Elrich, County Executive

9/20/19
Date

Approved as to form and legality:



Office of the County Attorney

9 August 2019
Date

Resolution No.: 19-272
Introduced: October 22, 2019
Adopted: October 22, 2019

**COUNTY COUNCIL
FOR MONTGOMERY COUNTY, MARYLAND**

Lead Sponsor: Council President at the request of the County Executive

SUBJECT: Executive Regulation 23-19, Adoption of the 2017 National Electrical Code

Background


1. On September 24, 2019, the Council received the County Executive's recommended Executive Regulation (ER) 23-19 as a Method 2 regulation. Under §2A of the County Code, this Method 2 regulation is "automatically approved" 60 days after the Council received it if the Council does not disapprove it or extend time by resolution before the 60-day period ends. The 60th day after September 24, 2019 is Saturday, November 23, 2019.
2. The Regulation would supersede Executive Regulation 6-16AM and adopt the 2017 National Electrical Code with minor amendments. ER 23-19 will be effective on October 22, 2019.
3. The Regulation would amend the regulation adopting the 2014 code by adopting the 2017 code, excluding smoke detectors as power-consuming devices for counting purposes, renaming "emergency panel" to "legally required stand by system", and making editorial changes.
4. Staff recommended approval of ER 23-19.

Action

The County Council for Montgomery County, Maryland approves the following resolution:

The County Council approves ER 23-19.

This is a correct copy of Council action.


Mary Anne Paradise
Acting Clerk of the Council